

ARRISOFT 2000



Cat. No. Description

536200	ARRISOFT 2000
536215	Egg Crate
536220	Filter Frame
536225	Soft-White Reflector (spare)
536226	Hard (Silver) Reflector
853276	Safety Cable
C02100	Baby Pipe Clamp (Required for hanging)

Lamps

Code	FCM	EME	EJG	FCM/HIR
Watts	1000	800	750	650
Volts	120	220	120	120
Color Temp (K)	3200	3200	3200	3200
Approx. Life (hrs)	400	250	400	400

Photometric Data with FCM 1000W Lamp

Distance	10 ft. (3.0 m)	12 ft. (3.7 m)	15 ft. (4.6 m)	20 ft. (6.1 m)
Horizontal Beam Angle 73°				
Vertical Beam Angle 71°				
Footcandles	71	49	32	18
Vertical Beam Spread	14.3 ft. (4.4 m)	17.1 ft. (5.2 m)	21.4 ft. (6.5 m)	28.6 ft. (8.7 m)

Performance at any distance:

Footcandles (or lux) = $7100 \div \text{Distance}^2$ Vertical Beam Spread = Distance x 1.43

Specifications

Weight	17 lbs (7.7 kg)
Cable	25 ft. (7.6 m)
Aperture	7.7" (195 mm) x 9.5" (241 mm)
Lampholder	R7S
Mounting	5/8" (16 mm) stand mount

